

# JBL 140Z Specs

## Power Amplifier

---

|                          |   |
|--------------------------|---|
| Number of Channels       | 1   |
| Power Rating             | <b>4 Ohms / 8 Ohms:</b><br>40 W (1 kHz, 0.5% THD) |
| Load Impedance / Voltage | 4 Ohms (Minimum)<br>70 / 100 V                    |

---

## Performance

---

|                    |   |
|--------------------|---|
| Frequency Response | 20 Hz to 20 kHz $\pm$ 0.5 dB (8 Ohms)                                   |
| Input Sensitivity  | 1.4 Vrms  |
| Input Impedance    | <b>Euroblock:</b><br>20 Kilohms (Balanced)<br><b>RCA:</b><br>50 Kilohms |
| SNR                | > 100 dB  |
| THD                | <0.5%   |
| Crosstalk          | > 70 dB   |

---

## Signal Processing

---

EQ 2-Band EQ ⓘ

---

## Connectivity

---

I/O 1 x 2RCA Summed-Mono Input  
1 x Euroblock Input  
1 x Euroblock Output

---

Digital I/O 1 x RJ45 (Control)

---

## Power

---

AC Input Power 100 to 240 VAC, 50 / 60 Hz

---

## Physical

---

Operating Temperature 32 to 95°F / 0 to 35°C

---

Storage Temperature -4 to 185°F / -20 to 85°C

---

Dimensions 8.6 x 11.9 x 1.7" / 218.5 x 303.4 x 43.3 mm

---

Weight 6.3 lb / 2.8 kg

---

## Packaging Info

---

Package Weight 10 lb

---

Box Dimensions (LxWxH) 16.2 x 12.1 x 5"

---