

JBL VMA260 Specs

| | |
|---------------------------------|---|
| Output Power | 60 W (per channel into 4 Ohms or 8 Ohms, 1 kHz, $\leq 0.5\%$ THD) |
| Insertion Loss | 70 V and 100 V Outputs: 1 dB maximum |
| Input Channels | 8 |
| Output Channels | 2 |
| Tone Controls | Bass and Treble non-detented potentiometers on each channel Bass: ± 14 dB @ 50 Hz Treble: ± 14 dB @ 10 kHz |
| Input Sensitivity | To obtain full rated power (load of 8 Ohms) Mic Input: 5.5 mVrms Line Input: 1.3 Vrms RCA Input (Stereo In): 130 mVrms |
| Frequency Response | Measured at 2.83 Vrms into rated load impedance at any output 4/8 Ohms Output: 20 Hz to 20 kHz, ± 2 dB 70 V/100 V Outputs: 80 Hz to 15 kHz ± 3 dB |
| Total Harmonic Distortion (THD) | Measured at 2.83 Vrms into rated load impedance at any output Power Amp Output: $< 0.5\%$, 20 Hz to 20 kHz |

| | |
|------------------------|--|
| Signal-to-Noise Ratio | >76 dB (reference rated power, mixer levels @ minimum, master volume @ maximum A-weighted) |
| Input Impedance | Nominal Mic: 400 Ohms Line: 20 kOhms (balanced) RCA: 50 kOhms |
| Phantom Power | 27 VDC |
| Crosstalk | -70 dB (reference rated power, volume at mid position, 1 kHz) |
| Nominal Input Voltages | Nominal AC Line Voltages: 100, 120, 220, 220 to 240 VAC, 50/60 Hz |
| Minimum Load Impedance | Low Impedance Output: 4 Ohms 70 V Output: 80 Ohms 100 V Output: 160 Ohms |
| Operating Temperature | 32 to 95°F / 0 to 35°C |
| Humidity | 95% RH (non-condensing) |
| Storage Temperature | -4 to 185°F / -20 to 85°C |
| Dimensions (W x D x H) | 17 x 16.3 x 3.5" / 432 x 415 x 88 mm |
| Weight | 25.5 / 11.6 kg |

Packaging Info

| | |
|----------------|-------|
| Package Weight | 30 lb |
|----------------|-------|

Box Dimensions (LxWxH)

21 x 20.5 x 7"
