

Behringer DI800 V2 Specs

Type	Active
Input Connections	8 x 1/4" / 6.35 mm TS, unbalanced and de-coupled
Output Connectors	8 x XLR, electronically balanced 8 x 1/4" / 6.35 mm TS, unbalanced 8 x 1/4" / 6.35 mm LINK (can also function as inputs)
Input Level	+18 dBu +48 dBu (-30 dBu pad depressed)
Output Level	+23 dBu, balanced +16 dBu, unbalanced
Input and Output Impedance	Input: 350 kOhms XLR Output: 1.36 kOhms balanced, 680 Ohms unbalanced Link Output (1/4"): 350 kOhms Unbalanced (1/4"): 950 Ohms
Controls	<i>Per Channel:</i> -30 dB Attenuation switch +20 dB Pad switch Ground-lift switch
Frequency Response	10 Hz to 50 kHz (± 3 dB)
Signal-to-Noise Ratio (SNR)	-96 dBu, (22 Hz to 22 kHz)
Distortion	

Power	Switch Mode Power Supply: Autorange 100 to 240 VAC, 50/60 Hz Power Consumption: 10 W Mains Connector: Standard IEC receptacle
-------	---

Dimensions (H x W x D)	1.7 x 19.0 x 5.3" / 4.4 x 48.3 x 13.4 cm
------------------------	--

Weight	4.0 lb / 1.8 kg
--------	-----------------

Packaging Info

Package Weight	5.1 lb
----------------	--------

Box Dimensions (LxWxH)	20.5 x 9.75 x 4.25"
------------------------	---------------------
