

# Behringer BEDI4000V2 Specs

## Audio Inputs

Connectors: 4 x XLR Female (Unbalanced) and 4 x 1/4" / 6.3 mm TS (Unbalanced)  
Type: DC-Decoupled, Unbalanced Input

Impedance: 240 Kilohms (Pad Out)

Max Input Level: +20/+40/+60 dBu at 1 kHz

---

## Audio Outputs

Connectors: 4 x XLR Male (Balanced) and 4 x 1/4" / 6.3 mm TS (Unbalanced)  
Type: Transformer-Balanced Output Stage on XLR

Impedance: 120 Ohms

Max Output Level: +20 dBu

---

## Frequency Response

Bandwidth (100 Kilohms Load): 23 Hz to 60 kHz ( $\pm 3$  dB)

Bandwidth (600 Ohms Load): 23 Hz to 40 kHz ( $\pm 3$  dB)

Bandwidth (High Cut): 23 Hz to 8 kHz (-3 dB)

---

## Noise

-90 dBu, 22 Hz to 22 kHz

---

## Distortion

---

## Crosstalk

-100 dBu at 1 kHz

---

## Power Supply

Switch-Mode Auto-Range Power Supply: 100-240 VAC, 50/60 Hz

Power Consumption: 10 W

Mains Connection: Standard IEC Connector

---

Dimensions (H x W x D)

1.7 x 19 x 5.4" / 44 x 483 x 136 mm, (1 RU)

---

Weight

4.6 lb / 2.1 kg

---