

Behringer SL4220-WH Specs

Transducers

| | |
|-----------------------|--|
| Nominal Impedance | 16 Ω |
| Low Frequency Driver | 4" at 45 W |
| High Frequency Driver | 3/4" at 3 W |
| Power Handling | 30 W, RMS (long term) |
| Maximum SPL | 101 dB @ 1.0 m (continuous, passive), 107 dB @ 1.0 m (peak, passive) |
| Enclosure | Plastic |

Loudspeaker

| | |
|--------------------|-----------------------------------|
| Frequency Range | 90 Hz to 20 kHz |
| Frequency Response | 120 Hz to 20 kHz |
| Nominal Dispersion | 120° |
| Directivity Factor | 6.0 (average 500 Hz to 16 kHz) |
| Directivity Index | 7.8 dB (average 500 Hz to 16 kHz) |

| | |
|------------------------|---|
| Sensitivity | 86 dB, 1 W @ 1 m passive, half-space |
| Crossover | Transformer, passive |
| Crossover Frequency | 2.2 kHz |
| Transformer | 70 V: 30 , 15 , 7.5 , 4 W 100 V: N/C, 30 , 15 , 7.5 W |
| Grille | Powder-coated steel |
| Termination | 4-pin Euroblock connector |
| Dimensions (H x W x D) | Approximately 9.1 x 5.9 x 5.7" (231.0 x 150.0 x 144.7 mm) |
| Weight | Approximately 4.4 lb (1.9 kg) |
