

Behringer NX1000 Specs

Power Amplifier

Number of Channels

2

Power Rating

2 Ohms:
500 W per Channel
4 Ohms:
300 W per Channel
1000 W Bridged
8 Ohms:
160 W per Channel
620 W Bridged

Amplifier Class

Class-D

Performance

Protections

DC Fault, On/Off Muting, Reactive/Mismatched Load, Thermal

Frequency Response

20 Hz to 20 kHz +0/-1 dB

Damping Factor

>155 at 8 Ohms

Input Sensitivity

0.78 V / 0 dBu

SNR

>100 dB

Distortion

Signal Processing

Crossover Yes

Connectivity

I/O **2 x** Combo XLR-1/4" Balanced/Unbalanced Input
2 x speakON Output

Power

AC Input Power 100 to 120 VAC, 50 / 60 Hz (T 6.3 A H 250 V)

AC Power Connector IEC

Power Consumption **2 Ohms:**
150 W (1/8 Power)

Physical

Display & Indicators **1 x** Amber LCD (Backlit)
1 x LED (Limit, per Channel)
1 x Multi-Segment LED Meter (per Channel)
1 x Red LED (Protect, per Channel)

Cooling Fan (Variable Speed)

Dimensions	3.7 x 19.0 x 9.1" / 94.0 x 483.0 x 231.0 mm ⓘ
------------	---

Weight	7.3 lb / 3.3 kg
--------	-----------------

Packaging Info

Package Weight	9.5 lb
----------------	--------

Box Dimensions (LxWxH)	22 x 12 x 6.5"
------------------------	----------------
