

# Behringer 502 Specs

Total # Of Inputs	5 Inputs
Mic/Line Inputs	<b>1 Mic:</b> 3-Pin XLR <b>5 Line:</b> 1/4" TRS Phone
Stereo Line Inputs	<b>2 Stereo:</b> L/R Paired 1/4" TRS Phone <i>channels 2/3 and 4/5</i>
In-Line Inputs>Returns	No
AUX Sends	No
AUX Returns	No
Inserts	No
BUS (Group) Outputs	<b>Stereo Main Only:</b> L/R 1/4" TRS Phone
2 Trk Master I/O	CD/Tape - <b>Input:</b> L/R RCA Phono <b>Output:</b> L/R RCA Phono
ALT I/O	No
Monitor Outputs	<b>Phones:</b> 1/4" Stereo
EQ Section	Low: 80 Hz +/- 15 dB High: 12 kHz +/- 15 dB

Solo/Mute	No
Channel Level Control	Rotary Controls
Trim/Gain Control	No
Phantom Power	Yes
Metering	Stereo: 4-segment Peak LED meters
Frequency Response	10 Hz to 20 kHz (-3 dB)
Dynamic Range	Not Specified by Manufacturer
Signal-to-Noise Ratio	110 dB / 112 dB A-weighted
Total Harmonic Distortion (THD)	0.005% / 0.004% A-weighted
Power Supply	13W USA/Canada 120 V~, 60 Hz, MXUL5 adapter
Dimensions (HxWxD)	1.85 x 5.27 x 6.97" (47 x 134 x 177 mm)
Weight	1.21 lb (0.55 kg)

## Packaging Info

---

Package Weight	3.245 lb
Box Dimensions (LxWxH)	11.85 x 8.9 x 3.5"

