

# Behringer F1320D Specs

## PA Speaker

---

Configuration Active 2-Way

---

Total Power Capacity 300 W

---

Amplifier Power Rating **LF:**  
160 W RMS  
225 W Peak (at 8 Ohms)  
**HF:**  
40 W RMS  
72 W Peak (at 8 Ohms)

---

## Performance

---

Frequency Response 60 Hz to 16 kHz -10 dB

---

Maximum SPL 115 dB

---

Input Sensitivity 0 to -50 dBu

---

I/O Impedance **Input:**  
20 Kilohms (Balanced)  
30 Kilohms (Unbalanced)

---

## Connectivity

---

Audio I/O	<b>1 x</b> XLR 3-Pin Mic/Line Input <b>1 x</b> 1/4" TRS Mic/Line Input <b>1 x</b> XLR 3-Pin Thru/Output <b>1 x</b> 1/4" TRS Thru/Output
-----------	--

---

## Signal Processing

---

EQ	<b>HF Shelf:</b> ±15 dB at 12 kHz <b>MF Notch/Peak:</b> ±15 dB at 2.5 kHz <b>LF Shelf:</b> ±15 dB at 80 Hz
----	---

---

Semi-Parametric EQ	-15 dB at 300 Hz to 6 kHz, Q: 20 ⓘ
--------------------	------------------------------------

---

Dynamic Processing	Optical Limiter
--------------------	-----------------

---

## Power

---

AC Input Power	120 VAC, 60 Hz (T 4 A H 250 V) 230 to 240 VAC, 50 Hz (T 2 A H 250 V) 220 VAC, 50 / 60 Hz (T 2 A H 250 V) 100 VAC, 50 / 60 Hz (T 4 A H 250 V)
----------------	---

---

AC Power Connector	<b>1 x</b> IEC
--------------------	----------------

---

Power Consumption	300 W (Max)
-------------------	-------------

---

## Physical

---

Dimensions 14.2 x 22.8 x 16" / 360 x 580 x 406 mm

---

Weight 34.5 lb / 15.7 kg

---

## Packaging Info

---

Package Weight 41 lb

---

Box Dimensions (LxWxH) 26.5 x 19 x 18"

---