

Behringer FBQ3102HD Specs

Filter Type	Graphic
Number of Channels	2x
Inputs	2x XLR 2x 1/4" TRS phone
Outputs	2x XLR 1x XLR for subwoofer 2x 1/4" TRS phone
THD & Noise	0.008%
Maximum Input Level	+21 dBu balanced and unbalanced
Indicators	LED input/output levels at -30, -24, -18, -12, -6, -3, 0, +6, +9, +12 dB, and CLIP
Frequency Bands	31 per channel, ISO frequencies
Bandwidth	1/3 octave
Range (Boost/Cut)	+/-6 dB or +/-12 dB, switchable
Frequency Response	10 Hz to 30 kHz
Frequency Range	20 Hz to 20 kHz in 1/3 octave bands

Signal to Noise Ratio	>94 dB @ +4 dBu, 22 Hz to 22 kHz
Crossover Control	Dedicated mono subwoofer output with adjustable crossover frequency (30 to 200 Hz)
Power Consumption	35 W
Mains Voltage	100 to 240 VAC, 50/60 Hz
Dimensions (H x W x D)	3.5 x 19.0 x 5.9" / 8.9 x 48.3 x 15.0 cm
Weight	4.4 lb / 2 kg

Packaging Info

Package Weight	6.05 lb
Box Dimensions (LxWxH)	20.3 x 8.9 x 5.7"