

Behringer SL3242FX-PRO Specs

Total # Of Inputs	32
Mic/Line Inputs	24 - XLR Microphone 32 - 1/4" TRS Phone Line
Stereo Line Inputs	4 - 1/4" TRS Stereo Line
In-Line Inputs>Returns	No
AUX Sends	2 AUX Sends - 1/4" TRS Phone 2 FX Sends - 1/4" TRS Phone
AUX Returns	2 AUX Returns - L/R 1/4" TRS Phone
Inserts	24 - 1/4" TRS Phone (mono inputs) 2 - 1/4" TRS Phone (main output)
BUS (Group) Outputs	4 - 1/4" TRS Phone
2 Trk Master I/O	Main Out - Stereo L/R 3-pin XLR Main Out - Stereo L/R 1/4" TRS Phone Mono Out - 1/4" Phone Phono/CTRL Room - Stereo Single 1/4" TRS Phone
ALT I/O	Foot Switch - 1/4" Phone
Monitor Outputs	Phono/CTRL Room - Stereo Single 1/4" TRS Phone
EQ Section	Mono Channels

Low - 80Hz +/- 15dB
Mid - 100Hz to 8kHz +/- 15dB
High - 12kHz +/- 15dB
Low Cut - 80Hz, 18dB/oct.

Stereo Channels

Low - 80Hz +/- 15dB
Low Mid - 400Hz +/- 15dB
High Mid - 3kHz +/- 15dB
High - 12kHz +/- 15dB

Solo/Mute

SOLO / PFL MUTE

Channel Level Control

Fader

Trim/Gain Control

Rotary Pots

Phantom Power

+48V Phantom Power

Metering

Peak LEDs

Frequency Response

< 10Hz - 70kHz +0dB / -1dB
< 10Hz - 130kHz +0dB / -3dB

Dynamic Range

Not Specified By Manufacturer

Signal-to-Noise Ratio

110dB / 112dB A-weighted

Total Harmonic Distortion (THD)

0.004% / 0.003% A-weighted

Power Supply

Power Consumption 50W
Fuse (100 - 240V~, 50/60Hz) T 2.0 A H 250V
Standard IEC Receptacle

Dimensions (WxHxD)

3.9 x 35.3 x 16.1" (100 x 896 x 410mm)

Weight

25.4 lbs (11.5kg)

Packaging Info

Package Weight

28.15 lb

Box Dimensions (LxWxH)

37.6 x 19 x 7.1"
