

Behringer EP2000 Specs

Power Amplifier

Number of Channels

2

Power Rating

8 Ohms:
400 W per Channel
1500 W Bridged
4 Ohms:
750 W per Channel
2000 W Bridged
2 Ohms:
1000 W per Channel

Performance

Frequency Response

20 Hz to 20 kHz +0/-1 dB (at Rated Power -10 dB)

Damping Factor

>300 at 8 Ohms

Input Sensitivity

1.15 V / 3.4 dBu

Input Impedance

10 Kilohms (Unbalanced)
20 Kilohms (Balanced)

Max Gain

32 dB

SNR

-100 dB

THD

Connectivity

I/O	2 x XLR Input 2 x 1/4" Input 2 x speakON Output 2 x Binding Post Pair Output ⓘ
-----	---

Power

AC Input Power	100 to 120 VAC, 50 / 60 Hz
Current Consumption	15 A
Power Consumption	1600 W

Physical

Display & Indicators	1 x LED (Power) 2 x LED (Clip) 2 x LED (Signal)
Cooling	Fan (Variable Speed)
Dimensions	3.5 x 19.0 x 15.8" / 88.0 x 483.0 x 402.0 mm
Weight	34.6 lb / 15.7 kg

Packaging Info

Package Weight 46.55 lb

Box Dimensions (LxWxH) 24 x 22 x 7"
