

# Behringer NX3000D Specs

## Power Amplifier

---

Number of Channels	2
Power Rating	<b>2 Ohms:</b> 1500 W per Channel <b>4 Ohms:</b> 900 W per Channel 3000 W Bridged <b>8 Ohms:</b> 440 W per Channel 1500 W Bridged
Amplifier Class	Class-D

---

## Performance

---

Protections	DC Fault, On/Off Muting, Reactive/Mismatched Load, Thermal
Frequency Response	20 Hz to 20 kHz +0/-1 dB
Damping Factor	>145 at 8 Ohms
Input Sensitivity	0.78 V / 0 dBu
Input Impedance	10 Kilohms (Unbalanced) 20 Kilohms (Balanced)

---

SNR	> 100 dB
-----	----------

---

Distortion	
------------	--

---

## Signal Processing

---

Audio Delay	Adjustable Up to 300 ms per Channel
-------------	-------------------------------------

---

Crossover	Yes
-----------	-----

---

EQ	8-Band Parametric EQ 2-Band EQ per Channel
----	---

---

Limiting	Peak, Zero-Attack (per Channel)
----------	---------------------------------

---

## Connectivity

---

I/O	<b>2 x</b> Combo XLR-1/4" Input <b>2 x</b> speakON Output
-----	--

---

USB	<b>1 x</b> USB Type-B (Control)
-----	---------------------------------

---

## Power

---

AC Input Power	100 to 120 VAC, 50 / 60 Hz (T 10 A H 250 V)
----------------	---

---

AC Power Connector	IEC
--------------------	-----

---

Power Consumption

**2 Ohms:**  
350 W (1/8 Power)

---

## Physical

---

Display & Indicators

**1 x** Amber LCD (Backlit)  
**1 x** LED (Limit, per Channel)  
**1 x** Multi-Segment LED Meter (per Channel)  
**1 x** Red LED (Protect, per Channel)

---

Cooling

Fan (Variable Speed)

---

Dimensions

3.7 x 19.0 x 9.1" / 94.0 x 483.0 x 231.0 mm ⓘ

---

Weight

7.9 lb / 3.6 kg

---

## Packaging Info

---

Package Weight

9.995 lb

---

Box Dimensions (LxWxH)

21.95 x 12 x 6.8"

---