

- Super high power single channel PA booster amplifier, specially designed for big installations where large number of speakers are required. Class H operation for optimum efficiency
- Line Input 200mV/1V switchable for connecting a mixer or another amplifier.
- 100V input for connecting to another amplifier 100V output.
- Built-in circuit for protection against overload, short circuit and temperature.
- Built-in protection against overvoltage in AC mains supply which is specially useful while operating on a genset.
- Box Speaker/Driver Unit selector switch. Bass boost defeated at Driver Unit position for safer operation of driver units.
- 100V/70V, 4W and 2W power outputs

<b>Power Output</b>	<b>3000W Max., 2500W RMS at 10% THD 2300W RMS at 5% THD, 2150W RMS at 2% THD</b>
<b>Output Regulation</b>	<b>≤ 2 dB, no load to full load at 1kHz</b>
<b>Input Channels</b>	<b>1 × Line 200mV/20kΩ balanced, 10kΩ unbalanced, 1 × Line 1V/20kΩ balanced, 10kΩ unbalanced, 1 × 100V Input/50kΩ</b>
<b>Frequency Response</b>	<b>50-15,000Hz ±3dB</b>
<b>Signal to Noise Ratio</b>	<b>75dB</b>
<b>Tone Controls</b>	<b>Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz</b>
<b>Speaker Outputs</b>	<b>2Ω, 4Ω, 70V &amp; 100V</b>
<b>Power Supply</b>	<b>AC: 220-240V 50/60Hz</b>
<b>Power Consumption</b>	<b>AC: 3400VA</b>
<b>Dimensions</b>	<b>W520 × H185 × D595 mm</b>
<b>Weight</b>	<b>38.50kg</b>