

High Wattage PA Power Amplifier

- Line Input 200mV/1V switchable for connecting a mixer or another amplifier.
- 100V input for connecting another amplifier output.
- Resettable circuit breaker for protection against overload and short circuit.
- Instant transfer to DC power (Car Battery) if AC power fails.
- Box Speaker/Driver Unit selector switch. Bass boost defeated at Driver Unit position for safer operation of driver units.
- Ideal for large installations where a high power output is required. A combination of a SSA-10000 and one SPA-10000 can deliver 2000W power output.

Power Output	1350W Max., 1000W RMS at 10% THD, 850W RMS at 5% THD, 800W RMS at 2% THD
Output Regulation	≤ 2 dB, no load to full load at 1kHz
Input Channels	1 × Line 200mV/100kΩ, 1 × Line 1V/50kΩ, 1 × 100V Input
Frequency Response	50-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz
Speaker Outputs	2Ω, 4Ω, 70V & 100V
Power Supply	DC: 48V (4×12V Car Battery) AC: 220-240V 50/60Hz
Power Consumption	DC: 12A AC: 1600VA
Dimensions	W540 × H185 × D510 mm
Weight	41.0kg