

AHUJA PA POWER AMPLIFIER BTZ-20000P

Brand	Ahuja
Model	Ahuja BTZ-20000A
Type	Amplifier
Amplifier Type	Ahuja DJ AND PA Amplifier
Power Output	1000W + 1000W RMS at 10% THD Rated, 900W + 900W RMS at 5% THD, 820W + 820W RMS at 2% THD
Input Channels	Mono 200mV / 100kW unbalanced input through Mono Phone Jack, 1V/50k Balanced input through stereo Phone Jack and XLR Connector Stereo Left Channel / A: 200mV / 100kW (through RCA Socket), Right Channel / B: 200mV / 100kW (through RCA Socket) Line Left Channel / A: 1V / 50kW, Right Channel / B: 1V/50kW (Both Balanced input through Stereo Phone Jack & XLR connector)
Output Regulation	≤ 2 dB, no load to full load at 1kHz
Frequency Response	50-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: ±8dB at 100Hz, Treble: ±8dB at 10kHz
Output	Mono: 200mV/100kW, Stereo: L/R 1V/1kW
Speaker Outputs	2Ω, 4Ω, 8Ω, 70V & 100V for each zone
Power Supply	AC: 220-240V 50/60 Hz
Power Consumption	AC: 2800VA
Dimensions	BTZ-20000A W560 × H165 × D530 mm
Weight	34.0kg
Number Of Items	1
Color	Black