

Yamaha DZR10 Dante-Equipped Specs

PA Speaker

Configuration	Active 2-Way
Enclosure Type	Bass-Reflex Loudspeaker
Total Power Capacity	2000 W Peak 950 W RMS
Amplifier Power Rating	LF: 1000 W Peak 850 W RMS HF: 1000 W Peak 100 W RMS
Amplifier Class	Class-D

Drivers

HF Driver	1 x Titanium Compression Driver with 1" / 25.4 mm Throat
HF Voice Coil	2" / 50.8 mm
LF Driver	1 x 10" / 25.4 cm Woofer
LF Voice Coil	3" / 76.2 mm
Magnet	HF: Neodymium LF: Neodymium

Performance

Frequency Range	44 Hz to 20 kHz -10 dB
Maximum SPL	137 dB
Coverage Angle	90° H x 60° V (Rotatable Horn) 60° H x 90° V (Monitor)

Max Input Level

Line Input:

+24 dBu

I/O Impedance

Input:

20 Kilohms

Connectivity

Audio I/O

2 x Combo XLR-1/4" TRS Female
Balanced/Unbalanced Input

2 x XLR 3-Pin Male Balanced Output

Network I/O

2 x etherCON (Dante)

USB

1 x USB Type-A (External Memory, Host Connection)

Signal Processing

Crossover

1.8 kHz

Max Sample Rate/Resolution

96 kHz

Power

AC Input Power	Universal: 100 to 240 VAC, 50 / 60 Hz
----------------	-------------------------------------------------

AC Power Connector	1 x IEC (Locking)
--------------------	--------------------------

Power Consumption	45 W (Idle) 150 W (1/8 Power)
-------------------	----------------------------------

Physical

Mounting	2 x 1.4" / 35 mm Pole Socket (Dual Angle, Bottom) 8 x M10 Fly Point 2 x M8 Fly Point
----------	-----------------------------------------------------------------------------------------------------------------

Monitor Angle	50°
---------------	-----

Handles	1 x Each Side
---------	----------------------

Cooling	Fan (Variable Speed)
---------	----------------------

Construction Material	Plywood
-----------------------	---------

Dimensions

12.4 x 21.1 x 13.6" / 315 x 535.9 x 345.4 mm

Weight

39.5 lb / 17.9 kg

Packaging Info

Package Weight

47 lb

Box Dimensions (LxWxH)

26.5 x 16.88 x 16.25"
