

Soundcraft EPM6 High Performance Audio Mixer (UK Version)

Compact 6 Mono + 2 Stereo Channel Analogue Audio Console with GB30 Preamps & UK Power Cable

01. PRODUCT OVERVIEW

The Soundcraft EPM6 (SKU: SCR-RW5734UK) is a high-performance, compact analogue mixing console designed for live sound reinforcement, recording studios, houses of worship, and multi-speaker AV installations.

Featuring Soundcraft's highly transparent GB30 microphone preamps, a 3-band EQ with swept mid-frequency control, and robust build quality, the UK version includes a standard UK 3-pin mains cable and internal universal power supply.

02. KEY FEATURES & HIGHLIGHTS

- 6 Mono + 2 Stereo Inputs:** 6 high-headroom mono mic/line channels plus 2 dedicated stereo line input channels.
- GB30 Preamp Technology:** Premium GB30 microphone preamps providing high headroom and precise gain structure (+55dB gain range).
- 3-Band EQ with Swept Mid:** Classic Soundcraft British EQ architecture with swept mid-frequency on mono channels.
- Dual Auxiliary Busses:** 2 configurable Aux sends (globally switchable pre/post fader) for stage monitors and external FX processors.
- Peak LED & 60mm Faders:** Pro-grade 60mm smooth-travel faders with proportional peak overload LED monitoring.

03. TECHNICAL SPECIFICATIONS

Part / SKU	SCR-RW5734UK
Mono Channels	6 x XLR / 1/4" TRS Jack
Stereo Channels	2 x Stereo Pairs (1/4" TRS Jack)
Mic Preamps	6 x GB30 Preamps (+48V Phantom)
EQ Architecture	3-band with swept mid (Mono), 2-band (Stereo)
Frequency Response	20 Hz – 20 kHz (+/- 1.5 dB)
THD & Noise	< 0.02% @ 1 kHz (Mic Gain +30dB)
Power Specification	Internal PSU with UK 3-Pin Power Cord

04. SYSTEM APPLICATIONS

Live Audio	Small Bands, Acoustic Duos, Solo Performers
Installations	Houses of Worship, Conference Rooms, Schools
Rackmount Option	Optional 19" Rack Ears (Sold Separately)

05. PHYSICAL SPECIFICATIONS

Console Dimensions	280 mm x 362 mm x 91 mm	Net Weight	approx. 4.0 kg (8.8 lbs)
Package Weight	approx. 5.2 kg (11.4 lbs)	Power Cable	Included UK BS1363 3-Pin Mains Lead

Operation Note: Global +48V Phantom Power switch controls all 6 mono XLR mic inputs simultaneously. Ensure phantom power is switched off when connecting dynamic microphones or unbalanced line devices.