

C1500

DLIVE REMOTE CONTROL SURFACE

The C1500 is a 12 fader dLive remote control Surface with 12" capacitive touchscreen.

The C1500 can control any MixRack / Mainframe. Up to 4 control Surface can be connected to a single MixRack / Mainframe.

12 faders & 12 rotaries are freely assignable in 6 layers on the surface, giving 72 control strips.

The dLive C1500 can be connected with a Single CAT5e cable to the MixRack / Mainframe.

With the C1500 surface you can choose the control for the end user through custom layouts and user permissions.



Key Features

- Mix and match with any MixRack
- Custom fader layout
- Self-locking Ethercon connectors
- Low noise, fanless design
- Compact 19" rack mountable

Benefits

- 12" Capacitive touchscreen
- 128x128 I/O port for extra audio networking
- User permissions
- 72 Control strips
- 19 User assignable keys