

# Allen & Heath ZEDI-10FX Specs

## Inputs & Outputs

---

Total # Of Inputs	12
XLR Audio Input	4 x XLR Inputs
Line In / Microphone In	4 x, Channels 1 through 4 4 x, Channels 5 and 6 (2 x Stereo Pair)
Instrument Input	2 X High Impedance
Main Output	2 x XLR
Monitor Output	2 x RCA
Line Output	1 x 1/4" (Headphones) 1 x 1/4" (Aux Out) 1 x 1/4" (FX Out)

---

## Digital Audio

---

Computer Connectivity	USB (Type B)
Digital I/O	4 x Input 4 x Output

---

Sample Rate and Resolution

Up to 24-bit/96 kHz

---

## Channels

---

EQ Section

3-Band (Channels 1 through 4)  
2-Band (Channel 5, Stereo)  
4 x High-Pass Filters (Channels 1 through 4)

---

Trim/Gain Control

5 x

---

Channel Level Controls

7 x

---

Phantom Power for Mic Inputs

4 x

---

## Dimensions & Weight

---

Dimensions (H x W x D)

3.8 x 13.1 x 10.8" / 96.5 x 332.7 x 274.3 mm

---

Weight

5.1 / 2.3 kg

---

## Packaging Info

---

Package Weight

7.4 lb

---

Box Dimensions (LxWxH)

18 x 13 x 5.5"

---

