

JBL 180Z Specs

Power Amplifier

| | |
|--------------------------|---|
| Number of Channels | 1 |
| Power Rating | 4 Ohms / 8 Ohms: 80 W (1 kHz, 0.5% THD) |
| Load Impedance / Voltage | 4 Ohms (Minimum) 70 / 100 V |

Performance

| | |
|--------------------|---|
| Frequency Response | 20 Hz to 20 kHz \pm 0.5 dB (8 Ohms) |
| Input Sensitivity | 1.4 Vrms |
| Input Impedance | Euroblock: 20 Kilohms (Balanced) RCA: 50 Kilohms |
| SNR | > 100 dB |
| THD | <0.5% |
| Crosstalk | > 70 dB |

Signal Processing

EQ 2-Band EQ ⓘ

Connectivity

I/O 1 x 2RCA Summed-Mono Input
1 x Euroblock Input
1 x Euroblock Output

Digital I/O 1 x RJ45 (Control)

Power

AC Input Power 100 to 240 VAC, 50 / 60 Hz

Physical

Operating Temperature 32 to 95°F / 0 to 35°C

Storage Temperature -4 to 185°F / -20 to 85°C

Dimensions 8.6 x 11.9 x 1.7" / 218.5 x 303.4 x 43.3 mm

Weight 6.9 lb / 3.1 kg

Packaging Info

Package Weight 10.4 lb

Box Dimensions (LxWxH) 16 x 12 x 5"
