

# JBL SRX812P Specs

## PA Speaker

---

Configuration	Active 2-Way
---------------	--------------

---

Total Power Capacity	2000 W Peak 1500 W RMS
----------------------	---------------------------

---

Amplifier Class	Class-D
-----------------	---------

---

## Performance

---

Frequency Response	48 Hz to 20 kHz -3 dB
--------------------	-----------------------

---

Maximum SPL	136 dB
-------------	--------

---

Coverage Angle	90° H x 50° V
----------------	---------------

---

Gain Range	<b>Line Input:</b> 21 dB
	<b>Aux Input:</b> 3 dB
	<b>Mic Input:</b> 45 dB
	<b>Line Input:</b> 20 dBu
	<b>Aux Input:</b> 8 dBu
	<b>Mic Input:</b> -4 dBu

---

I/O Impedance

**Input:**

40 Kilohms (Balanced)

20 Kilohms (Unbalanced)

---

## Connectivity

---

Audio I/O

**2 x** Combo XLR-1/4" TRS Input

**2 x** XLR 3-Pin Male Output

**1 x** XLR 3-Pin Mix Output

---

## Signal Processing

---

Crossover

1.9 kHz

---

## Power

---

AC Input Power

100 to 240 VAC, 50 / 60 Hz

---

Current Consumption

**120 VAC:**

2.2 A (1/8 Power)

5.6 A (1/3 Power)

---

## Physical

---

Mounting

**2 x** 1.4" / 36 mm Pole Socket

**12 x** M10

---

Handles	3
Cooling	Fan (Variable Speed)
Construction Material	Perforated Metal Grille, Plywood
Dimensions	25.1 x 16.3 x 16.9" / 63.8 x 41.5 x 42.9 cm
Weight	58 lb / 26.4 kg

## Packaging Info

---

Package Weight	66.5 lb
Box Dimensions (LxWxH)	27.3 x 22 x 21.5"