

JBL SRX818S Specs

PA Speaker

Configuration	Passive Subwoofer
---------------	-------------------

Total Power Capacity	2400 W Peak 1200 W Program 600 W RMS
----------------------	--

System Impedance	8 Ohms
------------------	--------

Drivers

LF Driver	1 x 18" / 457.2 mm Woofer
-----------	----------------------------------

Performance

Frequency Response	28 Hz to 150 Hz -10 dB 45 Hz to 150 Hz -3 dB
--------------------	---

Maximum SPL	135 dB
-------------	--------

Speaker Sensitivity	96 dB
---------------------	-------

Connectivity

Audio I/O	1 x speakON NL4 Input 1 x speakON NL4 Thru/Output ⓘ
-----------	--

Signal Processing

Crossover	80 Hz
-----------	-------

Physical

Mounting	1 x M20 (Top)
Handles	4
Construction Material	Perforated Metal Grille, Plywood
Dimensions	26.9 x 26.9 x 22.6" / 683 x 684 x 575 mm
Weight	78 lb / 35.4 kg
