

JBL SRX818SP Specs

PA Speaker

Configuration	Active Subwoofer
---------------	------------------

Total Power Capacity	1000 W Peak
----------------------	-------------

Amplifier Class	Class-D
-----------------	---------

Drivers

LF Driver	1 x 18" / 45.72 cm Woofer
-----------	----------------------------------

Performance

Frequency Range	29 Hz to 150 Hz -10 dB
-----------------	------------------------

Frequency Response	35 Hz to 120 Hz -3 dB
--------------------	-----------------------

Maximum SPL	135 dB
-------------	--------

Max Input Level	Line Input: 20 dBu
-----------------	------------------------------

Gain Range	Line Input:
------------	--------------------

21 dB

I/O Impedance

Input:

40 Kilohms (Balanced)

20 Kilohms (Unbalanced)

Connectivity

Audio I/O

2 x Combo XLR-1/4" Input

2 x XLR Output

Signal Processing

Crossover

80 Hz

Power

AC Input Power

100 to 240 VAC, 50 / 60 Hz

Current Consumption

2.2 A (1/8 Power)

5.6 A (1/3 Power)

Physical

Mounting

1 x M20 (Top)

Handles

4

Cooling	Fan (Variable Speed)
Construction Material	Perforated Metal Grille, Plywood
Dimensions	22.6 x 26.9 x 26.9" / 57.5 x 68.4 x 68.3 cm
Weight	87 lb / 39.5 kg

Packaging Info

Package Weight	107.1 lb
Box Dimensions (LxWxH)	32 x 32 x 25"