

## HP LaserJet Pro M402n { Specifications }

PRINT SPEED BLACK (ISO, A4)	Normal: Up to 38 ppm [4]
FIRST PAGE OUT (READY)	Black: As fast as 5.7 sec [5]
FIRST PAGE OUT (SLEEP)	Black: As fast as 8.1 sec [5]
PRINT QUALITY BLACK (BEST)	HP FastRes 1200
PRINT RESOLUTION TECHNOLOGIES	HP FastRes 1200, HP ProRes 1200, 600 dpi
DUTY CYCLE (MONTHLY, A4)	Up to 80,000 pages [6]
RECOMMENDED MONTHLY PAGE VOLUME	750 to 4000 [7]
PROCESSOR SPEED	1200 MHz
PRINT LANGUAGES	HP PCL 5, HP PCL 6, HP postscript level 3 emulation, direct PDF (v 1.7) printing, URF, PCLM, PWG
DISPLAY	2-line backlit LCD graphic display
REPLACEMENT CARTRIDGES	HP 26A Black LaserJet Toner Cartridge (~3100 pages), CF226A; HP 26X Black LaserJet Toner Cartridge (~9000 pages), CF226X [1]
HP EPRINT CAPABILITY	Yes
MOBILE PRINTING CAPABILITY	HP ePrint; Apple AirPrint™; Mopria™-certified; Google Cloud Print 2.0; Mobile Apps
WIRELESS CAPABILITY	No
CONNECTIVITY, STANDARD	1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network
NETWORK READY	Standard (built-in Gigabit Ethernet)
MINIMUM SYSTEM REQUIREMENTS	Windows 10 (32-bit/64-bit), Windows 8.1 (32-bit/64-bit), Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit): 1 GHz processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Vista (32-bit): 1 GHz 32-bit (x86) processor, 1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows XP (32-bit) SP2: Pentium 233 MHz processor, 512 MB RAM 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Server 2003 (32-bit) (SP1 or greater), Windows Server 2003 R2 (32-bit), Windows Server 2008 (32-bit) (SP1 or greater): 1 GHz 32-bit (x86) processor, 1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Server 2008 (64-bit) (SP1 or greater), Windows Server 2008 R2 (64-bit), Windows Server 2008 R2 (64-bit) (SP1): 1 GHz 64-bit (x64) processor, 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port
MINIMUM SYSTEM REQUIREMENTS FOR MACINTOSH	OS X 10.8 Mountain Lion; OS X 10.9 Mavericks; OS X 10.10 Yosemite; Internet; USB; 1 GB available hard disk space; OS compatible hardware (For OS hardware requirements see <a href="http://www.apple.com">http://www.apple.com</a> )
COMPATIBLE OPERATING SYSTEMS	Windows OS compatible with In-Box Driver: Windows XP SP3 all 32-bit editions (XP Home, XP Pro, etc), Windows Vista all 32-bit editions (Home Basic, Premium, Professional, etc.), Windows 7 all 32 & 64-bit editions, Windows 8/8.1 all

32 & 64-bit editions (excluding RT OS for Tablets), Windows 10 all 32 & 64-bit editions (excluding RT OS for Tablets); Windows OS compatible with Universal Print Driver (From HP.com): Windows XP SP3 32 & 64-bit editions (XP Home, XP Pro, etc.), Windows Vista all 32 & 64-bit editions (Home Basic, Premium, Professional, etc), Windows 7 all 32 & 64-bit editions, Windows 8/8.1 all 32 & 64-bit editions (excluding RT OS for Tablets), Windows 10 all 32 & 64-bit editions (excluding RT OS for Tablets); Mac OS (HP Print Drivers available from HP.com and Apple Store): OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite; Mobile OS (In-OS drivers): iOS, Android, Windows 8/8.1/10 RT; Linux OS (In-OS HPLIP); Auto install: BOSS (3.0, 5.0), DEBIAN (6.0, 6.0.1, 6.0.2, 6.0.3, 6.0.4, 6.0.5, 6.0.6, 6.0.7, 6.0.8, 6.0.9, 6.0.10, 7.0, 7.1, 7.2, 7.3, 7.4, 7.5, 7.6), FEDORA (17, 18, 19, 20), LINUX MINT (13, 14, 15, 16, 17), SUSE LINUX (12.2, 12.3, 13.1), UBUNTU (10.04, 11.10, 12.04, 12.10, 13.04, 13.10, 14.04, 14.10); Manual install: MANDRIVA LINUX (2010.0, 2011.0), MEPIS (6.0, 6.5, 7.0, 8.0), PCLINUXOS (2006.0, 2006, 2007.0, 2007, 2008.0, 2008, 2009.0, 2009), RED HAT (8.0, 9.0), RED HAT ENTERPRISE LINUX (5.0, 6.0, 7.0), SLACKWARE LINUX (9.0, 9.1, 10.0, 10.1, 10.2, 11, 12, 12.1), GOS (8.04.1), IGOS (1.0), LIMPUS LINUX(9.4, 9.5), LINUX FROM SCRATCH (6); Other OS: UNIX

OPERATING SYSTEM SUPPORTED FOOTNOTE NUMBER	[9]
MEMORY	128MB DRAM
MAXIMUM MEMORY	128MB DRAM
INTERNAL STORAGE	None
PAPER HANDLING OUTPUT, STANDARD	150-sheet output bin
PAPER HANDLING INPUT, OPTIONAL	Optional third 550-sheet tray
PAPER HANDLING INPUT, STANDARD	100-sheet multipurpose Tray 1, 250-sheet input Tray 2
MAXIMUM OUTPUT CAPACITY (SHEETS)	Up to 150 sheets
DUPLEX PRINTING	Manual(driver support provided)
MEDIA SIZES SUPPORTED	Tray 1: A4, A5, A6, B5 (JIS), Oficio, Oficio (216 x 340 mm), 16K (195 x 270 mm), 16K (184 x 260 mm), 16K (197 x 273 mm), Japanese Postcard, Double Japan Postcard Rotated, Envelope B5, Envelope C5, Envelope DL, Custom Size, A5-R, B6 (JIS); Tray 2 & Tray 3: A4, A5, A6, B5 (JIS), Oficio, Oficio (216 x 340 mm), 16K (195 x 270 mm), 16K (184 x 260 mm), 16K (197 x 273 mm), Custom Size, A5-R, B6 (JIS)
MEDIA SIZES, CUSTOM	Tray 1: 76.2 x 127 to 215.9 x 355.6 mm; Tray 2, 3: 104.9 x 148.59 to 215.9 x 355.6 mm
MEDIA TYPES	Paper (plain, EcoFFICIENT, light, heavy, bond, colored, letterhead, preprinted, prepunched, recycled, rough); envelopes; labels; transparencies
MEDIA WEIGHT, SUPPORTED	Tray 1: 60 to 175 g/m <sup>2</sup> ; Tray 2, Optional 550-sheet Tray 3: 60 to 120 g/m <sup>2</sup>
POWER	110-volt input voltage: 110 to 127 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz); 220-volt input voltage: 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz) (Not dual voltage, power supply varies by part number with #option code identifier)
POWER CONSUMPTION	591 watts (Active Printing), 6.1 watts (Ready), 2.8 watts (Sleep), 0.6 watts (Auto-On/Auto-Off, via USB connectivity), 0.1 watts (Shutdown or Off) [14]

OPERATING TEMPERATURE RANGE	15 to 32.5°C
RECOMMENDED OPERATING HUMIDITY RANGE	30 to 70% RH
ACOUSTIC POWER EMISSIONS (READY)	Inaudible [17]
ACOUSTIC PRESSURE EMISSIONS BYSTANDER (ACTIVE, PRINTING)	54 dB(A) [17]
MINIMUM DIMENSIONS (W X D X H)	381 x 357 x 216 mm [2]
MAXIMUM DIMENSIONS (W X D X H)	381 x 634 x 241 mm [2]
WEIGHT	8.58 kg [10]
PACKAGE DIMENSIONS (W X D X H)	443 x 274 x 464 mm
PACKAGE WEIGHT	11.36 kg
WHAT'S IN THE BOX	HP LaserJet Pro M402n; Preinstalled Introductory HP 26A Black LaserJet Toner Cartridge (~1500 pages); Getting Started Guide; Setup Poster; Support Flyer; Warranty Guide; Printer documentation and software on CD-ROM; Power cord; USB cable (AP Only)
WHAT IS IN THE BOX FOOTNOTE NUMBER	[18]
CABLE INCLUDED	Yes, 1 USB cable (AP only); No, please purchase USB cable separately (EMEA, Americas)
WARRANTY	1 Year Limited Warranty (Return to HP/Dealer - Standard Bench Repair)