

# Behringer AMP800 Specs

Number of Channels	4
Input Connections	4 x 1/4" TRS Phone (L,R Pairs), Balanced
Output Connectors	2 x 1/4" TRS Phone L,R Link, Balanced 4 x 1/4" TRS Headphone, Rear Panel 4 x 1/4" TRS Headphone, Front Panel
Maximum Output Level	+21dBm/124mW (100 Ohm load)
Function Controls	2 x A,B Input Balance Knobs 2 x A,B Input Level Knobs 4 x Individual Phones Level Knobs 4 x Channel Input Selector Switches 1 x Power Switch
Frequency Response	10 Hz - 120 kHz, -3dB
THD + N	0.007% (100 Ohm load)
Noise	
Display	6-segment LED Bargraphs
Dimensions	9.5 x 1.9 x 4.7" (242.6 x 48 x 120mm)
Weight	1.09 lb (494 g)
Specialties	Separate Front and Rear 4-Channel Headphone

Outputs  
Ultra-Compact  
Bargraph LED Metering

---

## Packaging Info

---

Package Weight	2.56 lb
----------------	---------

---

Box Dimensions (LxWxH)	15.35 x 6.9 x 4.05"
------------------------	---------------------

---