

# Behringer VMX100USB Specs

Number of Channels **2 x Stereo**

---

EQ **2 x Channel EQ:**  
Hi: -32 to +12 dB at 10 kHz  
Low: -32 to +12 dB at 50 Hz

---

Built-In Effects **Yes**

---

## Connectivity

---

Audio Inputs **2 x Stereo RCA Phono Input**  
**2 x Stereo RCA Line Input**

---

Audio Outputs **1 x Stereo RCA Master Output**  
**1 x Stereo RCA Record Output**

---

USB **1 x USB Type-B**

---

## Performance

---

Frequency Response **20 Hz to 20 kHz**

---

SNR **>88 dB**

---

## Compatibility

---

OS Compatibility	macOS Windows
------------------	------------------

---

## Power

---

AC Input Power	120 VAC, 60 Hz
----------------	----------------

---

AC Power Connector	<b>1 x IEC</b>
--------------------	----------------

---

Power Consumption	10 W (Maximum)
-------------------	----------------

---

## Physical

---

Dimensions (W x D x H)	8.0 x 9.0 x 2.8" / 203.0 x 229.0 x 72.0 mm
------------------------	--

---

Weight	4.4 lb / 2 kg
--------	---------------

---

## Packaging Info

---

Package Weight	6.8 lb
----------------	--------

---

Box Dimensions (LxWxH)	13 x 11 x 6"
------------------------	--------------

---