

Behringer NOX101 Specs

Number of Channels **2 x Stereo**

Faders **1 x Crossfader**
2 x Channel Level

EQ **Channel EQ:**
Low: -25 to +6 dB at 50 Hz
Mid: -30 to +6 dB at 1.2 kHz
Hi: -15 to +6 dB at 10 kHz
Mic EQ:
Low: ±12 dB at 50 Hz
Hi: ±12 dB at 12 kHz

Built-In Effects *None*

Connectivity

Audio Outputs **2 x 1/4" TRS Balanced Master Output**
2 x Stereo RCA Unbalanced Master Output

USB *None*

Performance

Frequency Response 10 Hz to 90 kHz +0/-3 dB

Gain/Trim Range **1/4" Mic Input:**

45 dB (Balanced)
RCA Line Input:
0 dB (Unbalanced)
RCA Phono Input:
35 dB (Unbalanced)

Output Level
1/4" Master:
18 dBu (Max)
RCA Master:
18 dBu (Max)

Headphone Output Power 566 mW into 75 Ohms (Max, 1 kHz)

Crosstalk >81 dB

SNR >89 dB

THD

Power

Power Adapter Output 9 VAC at 750 mA

Power Consumption 10 W

Physical

Dimensions (W x D x H) 10.0 x 10.8 x 3.9" / 255.0 x 274.0 x 100.0 mm

Weight 4.6 lb / 2.1 kg

Packaging Info

Package Weight 6.935 lb

Box Dimensions (LxWxH) 14.65 x 12.65 x 5.6"
