

# Behringer DX2000USB Specs

Number of Channels  
**5 x Stereo**  
**2 x Mic/Aux**

---

EQ  
**2 x Mic/Aux EQ:**  
Low:  $\pm 12$  dB at 50 Hz  
Mid:  $\pm 8$  dB at 750 Hz  
Hi:  $\pm 12$  dB at 10 kHz  
**5 x Channel EQ:**  
Low: -25 to +6 dB at 50 Hz  
Mid: -25 to +6 dB at 1.4 kHz  
Hi: -18 to +6 dB at 15 kHz

---

Performance Controls  
High-Pass Filter

---

Built-In Effects  
*None*

---

Sample Rates  
48 kHz

---

## Connectivity

---

USB  
**1 x USB Type-B**

---

## Performance

---

Frequency Response  
**Aux/Mic:**  
10 Hz to 8 kHz  $\pm 3$  dB  
**CD/Line:**  
10 Hz to 130 kHz  $\pm 3$  dB

**Phono:**  
20 Hz to 20 kHz (RIAA Curve)

---

Gain/Trim Range

**Mic Input:**  
+10 to +60 dB  
**Line Input:**  
-10 to +40 dB  
**Line/CD Input:**  
+17 / -20 dB  
**Phono Input:**  
+17 / -20 dB

---

Output Level

**1/4" Master:**  
0 dB  
**XLR Master:**  
+6 dB  
**Booth:**  
0 dB (Max)  
**Aux:**  
0 dB (Max)  
**Send:**  
0 dB

---

SNR

**Mic:**  
85 dB  
**CD/Line:**  
-82 dB  
**Phono:**  
-78 dB

---

THD

**Line/Mic Input:**  
0.08%  
**Stereo RCA CD/Line:**  
0.05%  
**Stereo RCA Phono:**  
0.1%

---

Compatibility

---

---

OS Compatibility	macOS Windows
------------------	------------------

---

## Power

---

AC Input Power	100 to 240 VAC, 50/60 Hz
----------------	--------------------------

---

Power Consumption	40 W
-------------------	------

---

## Physical

---

Dimensions (W x D x H)	17.2 x 14.0 x 6.0" / 440.0 x 356.0 x 152.0 mm ⓘ
------------------------	---

---

Weight	14.3 lb / 6.5 kg
--------	------------------

---

## Packaging Info

---

Package Weight	18.2 lb
----------------	---------

---

Box Dimensions (LxWxH)	22.2 x 17 x 8.2"
------------------------	------------------

---