

## Details

---

### **Ahuja SSA-100M 100 Watts High Power PA Amplifier.**

**Outputs :** Preamp 200mV/600Q, Line 1V/1kO

**Model No :** SSA-100M

**Tone Controls :** Bass:  $\pm 10$ dB at 100Hz, Treble:  $\pm 10$ dB at 10kHz

**Type of Product :** High Power PA Amplifier

**Speaker Outputs :** 40,80,70V & 100V

**Type :** Amplifier

**Power Consumption :** AC: 300VA DC: 4A

**Output Regulation :**  $\pm 2$  dB, no load to full load at 1kHz

**Signal to Noise Ratio:** 60dB

**Input Channels :** 5 x Mic 0.65mV/4.7k, 1 x Aux 50mV/470k 1 x Aux 150mV/470k

**Frequency Response :** 50-15,000Hz  $\pm 3$ dB

**Dimensions :** W420 x H155 x D320 mm

**Power Output :** 130W Max, 100W RMS at 10% THD, 90W RMS at 5% THD, 80W RMS at 2% THD

**Power Supply :** AC: 220-240V 50/60HZ DC: 24V (2x12V Car Battery)

**Watts :** 100 Watts