

- 4 Mic & 1 Aux Input. Built-in MP3 player with USB reader and remote control
- Line Output for connecting to a Booster Amplifier. Active Bass and Treble controls. Instant transfer to DC Power (Car Battery) if AC power fails.
- Power Supply AC: 220-240V 50/60Hz, DC: 12-14V Car Battery; Power Consumption AC: 140VA DC: 3A
- Power Output 100W Max., 75W RMS at 10% THD, 70W RMS at 5% THD. Output Regulation ≤ 2 dB, no load to full load at 1kHz
- Input Channels 4 \times Mic. 0.6mV/4.7k Ω , 1 \times Aux 100mV/330k Ω , Frequency Response 50-15,000Hz ± 3 dB, Signal to Noise Ratio 55dB
- Tone Controls Bass: -10dB +7dB at 100Hz, Treble: -10dB +7dB at 10kHz Outputs Line: 1V/3.5k Ω Speaker Outputs 4 Ω , 8 Ω , 16 Ω & 100V