

Ahuja introduces a 500 Watts Professional 2-Way PA Speaker System with Superior LF Response and Unmatched Sound Clarity.

- One 15" High Performance LF Transducer and a High Frequency Titanium Compression Horn Driver housed in an efficient and compact Bass Reflex Trapezoidal enclosure with superb paint finish.
- Strong and Sturdy Metal Grill provides protection to the speaker & enhances aesthetics of the painted cabinet.
- Well designed heavy duty metal handles ensure ease of handling and transportation.
- Suitable for both indoor and outdoor sound reinforcement applications Ideal for Auditoria... DJs... Live Concerts... Discos... etc
- **AHUJA** logo engraved on the both side of the cabinet lends uniqueness & freshness to the design and makes it difficult to imitate.

Specifications

INPUT POWER	500W RMS
CONFIGURATION	Two Way
FREQUENCY RESPONSE	35-20,000Hz
COMPONENTS	1 × 15" LF Speaker, 16" × 7" Dynamic HF Unit
SPL (1W/1m)	100dB
MAX. RATED SPL	127dB
NOMINAL IMPEDANCE	8Ω
CROSSOVER FREQUENCY	2kHz
PORT	Free Flow Flared
INPUT CONNECTORS	2 Nos. of Speakon Sockets
DIMENSIONS	W490 × H795 × D410mm
WEIGHT	40.00kg



500 WATTS 2 WAY

Design and Specifications are subject to change without notice owing to continuous product up-gradation. Technical specifications are subject to production tolerances. We cannot be held responsible for printing errors, should they occur. AHUJA is a registered trademark of Ahuja Radios in India and other countries. © Copyright Ahuja Radios, 2016. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law. No part of this compilation may be reproduced in any manner or translated without written permission.

AHUJA RADIOS

215, Okhla Industrial Estate, New Delhi - 110 020, INDIA Tel.: +91-11-26831549, 41612474 Fax: +91-11-26847287
E-mail: marketing@ahujaradios.com Website: www.ahujaradios.com

E. & O. E. 3K11116