

FEATURES

- PSX-1200 has a built-in Power Amplifier with multiple inputs for use in a wide variety of PA and Musical Instrument Programmes. Feature packed PSX-1200 is an ideal equipment for small as well as large gathering of around 200 people. Music and Vocal Performances, Conferences and Lectures, Presentations, Religious Discourses and Gatherings, Stage Monitors, Touring PA, Mini-Theaters, Pubs and Bars etc.
- 3 Microphone Inputs.
- Inputs for CD & Aux sources.
- 1 Keyboard Stereo Input with separate High & Low sensitivities.
- Send/return for connecting an Effects Processor.
- 2-Way Speaker System 12" Full Range Speaker + Piezo Horn.

SPECIFICATIONS

Power Output	100w RMS at 1% THD / 95W RMS at 0.5% THD
Output Regulation	0.5dB, no load to full load at 1kHz
Input Channels	3 — Mic 0.65 mV/4.7k 1 — Aux 100mV/470k 1 — Keyboard: 70mV/50k (Stereo Input) 750mV/50k (Stereo input)
Frequency Response	40-20,000Hz \pm 3dB
Signal To Noise Ratio	60dB
Tone Controls	Bass: \pm 5dB at 100Hz, Treble: \pm 5dB at 10kHz
Peamp Output	200mV/600
Send	250mV/1k
Return	250mV/47k
Protections	AC: Fuse 1 — 3A / DC: Fuse 2 — 5A
Power Supply	AC: 220-240V 50/60 Hz
AC Power Consumption	220VA
Dimensions	W420 — H550 — D420 mm
Weight	24.00kg