

FEATURES

- PSX-600 has a built-in power amplifier with multiple inputs for use in a wide variety of PA and musical instrument applications. It operate on both AC mains as well as 12V car battery making it ideal for use both indoors and outdoors. Ideal for Musical and Vocal Performances, Small Outdoor Gatherings, Religious Discourses, Lectures, Presentations.
- 50W Portable Public Address System with a top handle.
- Mic and Aux inputs. Active Tone Controls and Master Control.
- Preamp output for recording and connecting to an additional PSX-600.
- 2nos. 8" dual cone full range speakers. Stand mountable.
- Instant transfer to DC power (12V car battery) if AC power fails.

SPECIFICATIONS

Power Output 50W RMS at 5% THD 40W RMS at 1% THD

Output Regulation 2dB

Input Channels 2 — Mic 0.65mV/4.7k

(Mic source impedance 50 Ω -1k)

1 x Aux 100 mV/330k

Frequency Response 50-18,000Hz \pm 3dB

Signal To Noise Ratio 60dB

Tone Controls Bass: \pm 5dB at 100Hz Treble: \pm 5dB at 10kHz

Peamp Output 200mV/600

Protection Fuse AC 2A, DC 8A

Power Supply AC : 220V-240V 50/60Hz DC: 12V (12V Car Battery)

AC Power Consumption 100VA

Dimension W530 x H430 x D235 mm

Weight 15.50 kg