

Bose T8S TONEMATCH Specs

Mixer

Number of Analog Input Channels	8 (8 Mono / 0 Stereo)
Number of Mic Preamps	8
Number of Analog Output Channels	6
Max I/O Capacity	10 x Input / 6 x Output
Mix Routing	1 x Stereo Bus 4 x Mono Aux Send
Presets	Yes
Display	Main Display: LED
Faders	<i>None</i>
Meters	Channel Meter: 8 x Single LED Main Meter: 2 x LED

Signal Processing

Dynamic Processing Compressor, Limiter, Gate

EQ 3-Band EQ
3-Band Parametric

Graphic EQ *None*

Solo/Mute Mute per Input Channel

Internal Effects **3 x** Chorus
2 x Flanger
4 x Phaser
1 x Tremolo
3 x Delay
5 x Reverb

Real Time Analyzer *None*

Audio Delay *None*

Automatic Mic Mixing *None*

Digital Audio

Sample Rates 48 kHz

Bit Depth 24-Bit

Performance

Signal Generator *None*

Connectivity

Analog Inputs **8 x** Combo XLR-1/4" TRS Balanced/Unbalanced Mic/Hi-Z Input
2 x 1/4" TRS Balanced/Unbalanced Aux Input

Analog Outputs **2 x** 1/4" TRS Balanced Main Output
2 x XLR Main Output
4 x 1/4" Aux Send
1 x 1/4" Headphone Output

Phantom Power +48 V, Selectable On/Off

Digital I/O **1 x** RJ45

MIDI I/O *None*

USB **1 x** USB Type-A (USB 2.0, Audio Playback)
1 x USB Type-B (USB 2.0, Audio Streaming, Host Connection)

Expansion Ports *None*

Wireless Connectivity *None*

External Display Connection *None*

Recording

Media Support

USB Drive

File Format Support

Playback: MP3, WAV

Compatibility

OS Compatibility

macOS
Windows

Physical

Dimensions

3.3 x 12.3 x 8.4" / 82.6 x 311.2 x 213.4 mm

Weight

4.1 lb / 1.9 kg

Packaging Info

Package Weight

7.165 lb

Box Dimensions (LxWxH)

15.55 x 10.45 x 6.7"
