

PRODUCT HIGHLIGHTS

ClearOne's Wireless Microphone System is the most economical, versatile, and easily scalable wireless system in the market today with unprecedented ease-of-use and simple installation.

This microphone system complements other professional audio products from ClearOne including CONVERGE® Pro 1 & 2 Mixers, INTERACT Mixers, CONVERGE Matrix products. WS800 Receiver comes with and without Dante™ built-in audio networking.

Minimum Operating Frequency: 486 MHz
Maximum Operating Frequency: 512 MHz
Signal to Noise Ratio (SNR): 109 dB(A)
Operating Range: 300 ft
6.35mm (1/4"): Yes

Height: 1.8"
Width: 19"
Depth: 6.5"
Weight (Approximate): 4.70 lb

SPECIFICATIONS

General Information

Manufacturer	ClearOne
Manufacturer Part Number	910-6000-804-C-D
Manufacturer Website Address	http://www.clearone.com
Brand Name	ClearOne
Product Model	WS880
Product Name	WS880 8-Channel Wireless Microphone System Receiver
Product Type	Wireless Microphone System Receiver

Technical Information

Minimum Operating Frequency	486 MHz
Maximum Operating Frequency	512 MHz
Signal to Noise Ratio (SNR)	109 dB(A)
Operating Range	300 ft

Interfaces/Ports

6.35mm (1/4")	Yes
---------------	-----

Power Description

Input Voltage Range	100 V AC to 240 V AC
---------------------	----------------------

Miscellaneous

Additional Information	Dante Network Capability
------------------------	--------------------------

Overview

ClearOne WS880 8-Channel Wireless Microphone System Receiver

486 MHz to 512 MHz Operating Frequency - 300 ft Operating Range

ClearOne's Wireless Microphone System is the most economical, versatile, and easily scalable wireless system in the market today with unprecedented ease-of-use and simple installation.

This microphone system complements other professional audio products from ClearOne including CONVERGE® Pro 1 & 2 Mixers, INTERACT Mixers, CONVERGE Matrix products. WS800 Receiver comes with and without Dante™ built-in audio networking.

Gallery

