

# Roland Dante Specs

Channels	64 Channels at 48 kHz 32 Channels at 96 kHz
Sampling Frequencies	44.1, 48, 96 kHz
Depth	24-Bit
Connectors	Primary Port: RJ-45 XLR Secondary Port: RJ-45 XLR Control Port: RJ-45 USB Port: USB Type-B (Updates Only)
LED Indicators	3 x LINK/ACT 1 x 1G
Power Consumption	5 W
Operating Temperature	41 to 104°F / 5 to 40°C
Dimensions	4.8 x 7.3 x 1.6" / 12 x 18.5 x 4 cm
Weight	7 oz / 198 g

## Packaging Info

Package Weight	1.2 lb
Box Dimensions (LxWxH)	12.2 x 9.4 x 3.5"