

Details

Xerox B1025

Printer Size: A3

Resolution [DPI]: up to 1200

Black Print Speed [ppm]: 25

First Page Print [sec]: 8.9

Max. monthly load [str]: 50,000

Memory [GB]: 1.5

Duplexing: Yes

Tray Capacity [p]: 100 Bypass Tray, 250 Tray 1

Interface: 10/100Base-T Ethernet, Hi-Speed USB 2.0, Wi-Fi Direct® with optional Wi-Fi Kit

Print Languages: PCL6, Adobe PostScript

Starting Toner Capacity [p]: 2500

Scanner:

- **Speed:** 30 ipm
- **Resolution:** 600 x 600
- **Bit depth:** 24-bit color/8-bit black

Fax:

- **Speed:** 33.6 Kbps
- **Resolution:** Standard Resolution: 8 x 3.85 pixels/mm (203 x 98 dpi) Fine: 8 x 7.7 pixels/mm (203 x 196 dpi) Superfine: 11.8 x 11.8 pixels/mm (300 x 300 dpi)
- **Compression:** MH, MR, MMR, JBIG, JPEG
- **Features:** Walk-up Fax, Direct Fax

Power Consumption [W]: 80

Consumption Standby [W]: 1.5

Noise [dB]: 46/30 Preparation/Ready

Dimensions [HxWxD mm]: 505.7 x 560 x 598.6

Weight [kg]: 30.4

Supported Operating Systems:

Windows®, 7, 8, 10, Server 2000, Server 2003, Server 2008, Server 2008 R2 Server 2012

Mac OS® version 10.10, 10.11, 10.12

Citrix

Redhat® Enterprise

Linux®

IBM® AIX® 7.2

HP-UX® 11iv3

Oracle® Solaris 11.3

SUSE® 13.2