ViS HQ Mic Card (Channels 17-32)

16-Channel High-Quality Microphone Input Expansion Card for Soundcraft Vi2000 & Vi3000 Consoles

SKU / Part Number: 5045892.v **Module Type:** High-Quality (HQ) Mic Input Card **Status:** Packed Tested Spare

PRODUCT OVERVIEW

The **Soundcraft ViS HQ Mic Card 17-32 (SKU: 5045892.v)** is a 16-channel high-quality analog microphone input expansion card engineered specifically for the **Soundcraft Vi2000 and Vi3000** digital mixing consoles.

Featuring Soundcraft's flagship High-Quality (HQ) preamp circuitry, 24-bit A/D converters, and ultra-wide dynamic range, this card provides pristine audio transparency for channels 17 through 32 on the rear panel of the console chassis. It includes full remote console surface control for gain, phase, and switchable +48V phantom power.

KEY FEATURES

- **16 High-Quality (HQ) Mic Preamps:** Delivers pristine, ultra-low-noise analog amplification with high common-mode rejection.
- **Dedicated Slot Config (Channels 17–32):** Addressed specifically for the secondary local mic input bank in Vi2000 / Vi3000 console frames.
- **24-bit / High-Precision A/D Conversion:** Ensures transparent digital conversion preserving subtle acoustic nuances.
- **Remote Console Surface Integration:** Direct gain adjustment, phase reverse, and per-channel +48V phantom power control.
- **Direct Chassis Integration:** Fits internal expansion slots of Vi2000 and Vi3000 console frames.
- **Packed Tested Spare:** Factory-inspected and tested spare piece for immediate field replacement or console maintenance.

APPLICATIONS

- Replacing or expanding internal local microphone input channels (Ch 17–32) on Soundcraft Vi2000 and Vi3000 consoles.
- High-end live sound reinforcement, touring, theater, and broadcast facilities requiring top-tier local analog inputs.

TECHNICAL SPECIFICATIONS

SPECIFICATION HIGHLIGHTS	
Manufacturer	Soundcraft (HARMAN)
SKU / Part No.	5045892.v
Model Name	ViS HQ Mic Card (17-32)
Channel Mapping	Channels 17 to 32
Preamplifier Type	Soundcraft HQ (High-Quality)
Phantom Power	+48V (Switchable per channel)
A/D Conversion	24-bit / 48kHz / 96kHz capable
System Compatibility	Soundcraft Vi2000 & Vi3000 Consoles
Condition	Packed Tested Spare

COMPATIBILITY NOTICE

Specifically configured for Channels 17–32 in Soundcraft Vi2000 and Vi3000 mixing consoles. Ensure the console is powered off before replacing internal cards.

Soundcraft and Vi Series are registered trademarks of Soundcraft / HARMAN International Industries, Inc. Specifications subject to change without notice.